



D3

3-channel RGB LED dimmer · WiFi

One RGB strip or three single-colour zones, in a mini format.

3

PWM CHANNELS

12-24

VDC

1

INPUT

mini

WALL BOX

PART NUMBER **S-DW003**FAMILY **LED dimming**FIRMWARE **4.3.14**


Product overview

The D3 dims 3 constant-voltage LED strip channels (12-36 VDC) and reads 1 push-button, powered from the LED supply and connected over WiFi.

WHO IT IS FOR

Professional integrator. Integrates with Savant, Crestron Home, RTI, Vantage and URC through native drivers, and with KNX and Modbus without gateways. Compact installation with no dedicated bus.

Home. Appears in Apple Home, Google Home and Amazon Alexa through Matter, with no cloud or vendor account. Set up from a phone in five minutes.



WHAT YOU GET

- ✓ Full configuration from a browser, no app. Own access point for first commissioning.
- ✓ Push-button gestures: single, double, triple and long press, each with its own action.
- ✓ Local automations: input → output, scenes, URL calls. They work without the network.
- ✓ KNX over IP, Modbus TCP, Matter and HTTP API.
- ✓ Native drivers for Savant, Crestron Home, RTI, Vantage and URC.
- ✓ Firmware updates from the web interface, stable and beta channels, no cloud or account.
- ✓ Optional restore of the last state after a power cut.

WHAT IT DOES NOT DO

- Does not dim 230 V luminaires: it is not a phase-cut dimmer.
- Not 0-10 V or DALI.
- Does not measure energy.
- No Ethernet or PoE.

INTEGRATION



Matter